



## PSH-Series



## FEATURES

- \* Wide Input Voltage Range and High Power Factor (P.F)
- \* High Efficiency and High Power Density
- \* Constant Voltage and Constant Current Operation
- \* Over Voltage , Over Current and Over Temperature Protection
- \* Self-Test and Software Calibration
- \* Output ON/OFF Control
- \* Low Ripple and Noise
- \* LCD Display
- \* Built-in Buzzer Alarm
- \* Standard Interface : RS-232C
- \* Optional Interface : GPIB ( IEEE-488.2 )
- \* LabVIEW Driver

## Front Panel



## Rear Panel



The PSH-Series are single output from 360 to 1080W, programmable switching DC power supplies. OVP, OCP and OTP protect the power supply and loads from unexpected conditions. Remote sensing adds an extra level of precision by compensating cable losses between loads. The bright LCD with simultaneous parameter outputs allows effortless operation. Self-test and software calibration features also reduce maintenance overheads. SCPI commands and LabVIEW driver access through the RS-232C or the optional GPIB interface allow remote control and ATE software development capability. Modular architecture, dedicated rear-panel output, and the 19 inch 4U rack mounting option ensure that the PSH-Series is optimized for large systems.

## SPECIFICATIONS

OUTPUT				
10V	36A(PSH-1036A)	70A(PSH-1070A)	100A(PSH-10100A)	
20V	18A(PSH-2018A)	35A(PSH-2035A)	50A(PSH-2050A)	
36V	10A(PSH-3610A)	20A(PSH-3620A)	30A(PSH-3630A)	
60V	6A(PSH-6006A)	12A(PSH-6012A)	18A(PSH-6018A)	
REGULATION ( CV )				
Load	≤ 0.1%+5mV	≤ 0.1%+5mV	≤ 0.1%+5mV	
Line	≤ 0.05%+5mV	≤ 0.05%+5mV	≤ 0.05%+5mV	
REGULATION ( CC )				
Load	≤ 0.2%+5mA	≤ 0.2%+10mA	≤ 0.2%+15mA	
Line	≤ 0.2%+5mA	≤ 0.2%+10mA	≤ 0.2%+15mA	
RIPPLE & NOISE				
Voltage (mVrms)	≤ 10mVrms	≤ 10mVrms	≤ 10mVrms	
Voltage (mVp-p)	≤ 100mVp-p 20Hz~20MHz	≤ 100mVp-p 20Hz~20MHz	≤ 100mVp-p 20Hz~20MHz	
Current (mArms)	≤ 0.2%	≤ 0.2%+20mA	≤ 0.2%+40mA	
RESOLUTION				
Voltage	≤ 36V 10mV	10mV	10mV	
	>36V 20mV	20mV	20mV	
Current	10V 10mA	20mA	30mA	
	20V 10mA	10mA	20mA	
	36V 10mA	10mA	10mA	
	60V 10mA	10mA	10mA	
PROGRAM ACCURACY				
Voltage	≤ 36V	≤ 0.05%+25mV	≤ 0.05%+25mV	≤ 0.05%+25mV
	>36V	≤ 0.05%+50mV	≤ 0.05%+50mV	≤ 0.05%+50mV
Current	10V	≤ 0.2%+30mA	≤ 0.2%+60mA	≤ 0.2%+90mA
	20V	≤ 0.2%+30mA	≤ 0.2%+30mA	≤ 0.2%+60mA
	36V	≤ 0.2%+30mA	≤ 0.2%+30mA	≤ 0.2%+30mA
	60V	≤ 0.2%+30mA	≤ 0.2%+30mA	≤ 0.2%+30mA
READBACK ( Meter ) RESOLUTION				
Voltage	Same as Resolution	Same as Resolution	As Resolution	
Current	Same as Resolution	Same as Resolution	As Resolution	
READBACK ( Meter ) ACCURACY				
Voltage	Same as Program Accuracy	Same as Program Accuracy	As Program Accuracy	
Current	Same as Program Accuracy	Same as Program Accuracy	As Program Accuracy	
READBACK TEMP. COEFFICIENT				
Voltage (25±5°C)	≤ 100ppm/°C	≤ 100ppm/°C	≤ 100ppm/°C	
RESPONSE ( Rise/Fall ) TIME				
Voltage Up(10%~90%)	≤ 150mS(≤95% rating load)	≤ 150mS(≤95% rating load)	≤ 150mS(≤95% rating load)	
Voltage Down(90%~10%)	≤ 150mS(≥10% rating load)	≤ 150mS(≥10% rating load)	≤ 150mS(≥10% rating load)	
RECOVERY TIME ( 50% Step Load Change From 25%~75% )				
CV Mode	≤ 2mS	≤ 2mS	≤ 2mS	
PROTECTION				
OVP/OCP/OTP	✓	✓	✓	
Rush Current	✓	✓	✓	
OUTPUT ON/OFF CONTROL				
	✓	✓	✓	
INTERFACE				
Standard : RS-232C; Optional : GPIB				
POWER SOURCE				
AC90V~250V, 50/60Hz				
DIMENSIONS & WEIGHT				
	108(W)x142(H)x393(D)mm Approx. 3.3kg	188(W)x142(H)x393(D)mm Approx. 6.2kg	268(W)x142(H)x393(D)mm Approx. 9.3kg	

## ORDERING INFORMATION

<b>PSH-1036A</b> 360W Programmable Switching D.C. Power Supply	<b>PSH-3610A</b> 360W Programmable Switching D.C. Power Supply
<b>PSH-1070A</b> 700W Programmable Switching D.C. Power Supply	<b>PSH-3620A</b> 720W Programmable Switching D.C. Power Supply
<b>PSH-10100A</b> 1000W Programmable Switching D.C. Power Supply	<b>PSH-3630A</b> 1080W Programmable Switching D.C. Power Supply
<b>PSH-2018A</b> 360W Programmable Switching D.C. Power Supply	<b>PSH-6006A</b> 360W Programmable Switching D.C. Power Supply
<b>PSH-2035A</b> 700W Programmable Switching D.C. Power Supply	<b>PSH-6012A</b> 720W Programmable Switching D.C. Power Supply
<b>PSH-2050A</b> 1000W Programmable Switching D.C. Power Supply	<b>PSH-6018A</b> 1080W Programmable Switching D.C. Power Supply

## ACCESSORIES :

User manual x 1 , Power cord x 1

## OPTION

Opt. 01: GPIB Interface ( Factory Installed)

## OPTIONAL ACCESSORIES

**GRA-403** Rack Adapter Panel

**CTL-232** RS232C Cable, 9-pin Female to 9-pin, null Modem for Computer

## FREE DOWNLOAD

**PC Software Driver** PC Software including Data Log ; Remote Control Software  
Labview Driver

NOTE : When Opt.01 GPIB interface is ordered, the standard interface RS-232C will be deleted.